
Subject: diagrami: Simple Diagrammer for IDL & PV-Wave Language Programs
Posted by grunes on Wed, 08 Mar 1995 18:17:26 GMT

[View Forum Message](#) <> [Reply to Message](#)

Archive-name: diagrami

Submitted-by: grunes@nrlvax.nrl.navy.mil (Mitchell R Grunes)

****diagrami: Simple Diagrammer for IDL & PV-Wave Language Programs****

This is an update, which fixes minor bugs.

Sorry, little or no help can be provided for this program--
and I would need an example of where it failed.

-----CUT HERE-----

program diagrami !Diagrammer for IDL and PV-Wave

c EXAMPLE OF OUTPUT:

```
c   +-----pro Sample,a,b,c          |  1
c   |     a=indgen(15)^2            |  2
c   |+-----if a eq b then begin    |  3
c   ||     print,'A equals B'      |  4
c   ||     c=0                      |  5
c   |+-----else begin            |  6
c   ||     print,'A does not equal B' |  7
c   ||     c=1                      |  8
c   |+-----endif                  |  9
c   +-----end                     | 10
```

c Diagrams IDL and PV-Wave begin(or case)-end constructs, functions
c and procedures, places a * next to goto and return statements.

c

c Program by Mitchell R Grunes, ATSC/NRL. Revision date: 3/6/95.

c This program was written in FORTRAN, the One True Language.

c Note--this is a quick and dirty attempt--may not always work quite right.

c It does not yet handle CASE instances, since I don't use them myself,
c but it should draw a line around the entire CASE block.

c It is assumed that no fortran carriage control exists on the output
c file, so don't specify output to the screen or a terminal.

c I hope this works for you, but bear in mind that nothing short of
c a full-fledged language parser could really do the job. Perhaps
c worth about what you paid for it. (-:

c Versions: To diagram Fortran: diagramf.for

c IDL: diagrami.for
c C: diagramc.for

```
character*160 a,b
character*16 aa
character*5 form,fm
character*1 c
logical find
external find
common icol
print*,IDL source filename?
a=' '
read(*,1)a(1:132)
1 format(a132)
open(1,file=a,status='old')
print*,output file?
b=' '
read(*,1)b(1:132)
open(2,file=b,status='unknown')

c last minute change to reduce spaces in diagram block:
c print*,column for line #(60 for screen,91 for laser,112 for print,0 for none)?
c print*,column for line #(68 for screen,0 for none)?
iline=0
read*,iline
cwrite(2,*)a
cwrite(2,*)"*****"
aa='|||||||||||||||||||||'
i1=0      !# of nest levels before current line
i2=0      !# of nest levels on current line
i3=0      !# of nest levels after current line
i4=0      !1 to flag start or end of block
InSub=0    !Inside a subroutine or function?
nMainEnd=0 !# of mainline programs ended so far
nline=0
icontinue=0 !Not continued from previous line
10 read(1,11,end=99)a
11 format(a160)
nline=nline+1
if(nline/100*100.eq.nline)print*,Line ',fm(nline)

b=' '      !turn tabs to spaces
j=1
do i=1,160
  if(a(i:i).eq.char(9))then
    j=(j-1)/8*8+8+1
  elseif(j.le.160)then
    b(j:j)=a(i:i)
```

```

j=j+1
endif
enddo
i=1
j=1
a=' '
iquote=0      !no ' yet
idquote=0     !no " yet
j=1
do i=1,160
  c=b(i:i)
  if(c.ge.'A'.and.c.le.'Z')c=char(ichar(c)+32)
  if(c.eq.')")goto 15
  if(c.eq.("")iquote=1-iquote
  if(c.eq.("")idquote=1-idquote
  if(iquote.ne.0.or.idquote.ne.0)c=' '
  if(j.gt.1)then      !(kill multiple spaces)
    if(c.eq.' '.and.a(j-1:j-1).eq.' ')j=j-1
  endif
  a(j:j)=c
  j=j+1
enddo
15  i2=i1
i3=i1
iflag=0      !no goto on line
if(find(a,'goto',8+32).or.find(a,'return',1+128))iflag=1
if(find(a,'endif ',2).or.find(a,'endfor ',2)
& .or.find(a,'endelse ',2).or.find(a,'endwhile ',2)
& .or.find(a,'endcase ',2).or.find(a,'endrep ',2))then
  i3=i3-1
  i4=i4+1
  if(find(a,'begin ',1))i3=i3+1
  elseif(find(a,'case ',1))then
    i4=i4+1
    i2=i2+1
    i3=i3+1
  elseif(find(a,'begin ',1))then
    i4=i4+1
    i2=i2+1
    i3=i3+1
  elseif(find(a,'function ',2).or.find(a,'pro ',2))then
    if(lnSub.eq.0)then
      lnSub=1
      i2=i2+1
      i3=i3+1
      i4=i4+1
      if(i3.ne.1)then
        PRINT*,***ERROR--INVALID DIAGRAMMING INDEX line',

```

```

&      fm(nline)
      WRITE(2,*)"***ERROR--INVALID DIAGRAMMING INDEX!***"
      print*,char(7)
      endif
      endif
      i3=1
      elseif(find(a,'end ',2))then
          if(i3.gt.0.or.lnsub.gt.0)then      !Problem: IDL end may actually
              i3=i3-1                      ! be an endif, endelse, etc.
          i4=i4+1
          if(i3.eq.0.and.lnsub.ne.0)lnsub=0
          if(find(a,'begin ',1))then
              i2=i2+1
              i3=i3+1
          endif
      else
          nMainEnd=nMainEnd+1
          print*, '***MAINLINE END line ',fm(nline)
          if(nMainEnd.gt.1)then
              PRINT*, '***ERROR--TOO MANY MAINLINE ENDS!***'
              WRITE(2,*)"***ERROR--TOO MANY MAINLINE ENDS!***"
              print*,char(7)
          endif
      endif
      endif
      icontinue=0
      if(find(a,'$',0))icontinue=1
      a=' '
      if(i1.lt.0.or.i2.lt.0.or.i3.lt.0.or.i4.lt.0)then
          PRINT*, '***ERROR--INVALID DIAGRAMMING INDEX line',fm(nline)
          WRITE(2,*)"***ERROR--INVALID DIAGRAMMING INDEX!***"
          print*,char(7)
          i1=max(i1,0)
          i2=max(i2,0)
          i3=max(i3,0)
          i4=max(i4,0)
      endif
      jj=max(1,min(16,2*i2-1))
      if(i2.gt.0)a=aa(1:jj)
      if(i4.ne.0)then
          jjj=1
          dowhile(jjj.lt.160.and.b(jjj:jjj).eq.' ')
              jjj=jjj+1
          enddo
          if(jjj.gt.1)b(1:jjj-1)=
&      '-----'
      &      a(jj:16)='-----'
      endif

```

```

do i=0,i4-1
  a(max(1,min(15,jj-i*2)):max(1,min(15,jj+1-i*2)))='+-'
enddo
i4=0
if(iine.ne.0.and.b(max(1,iine):160).eq.' ')then
  form=fm(nline)           !line #
  if(form(1:1).eq.' ')form(1:1)='|'
  b(iine:iine+4)=form
endif
n=160
dowhile(n.gt.1.and.b(n:n).eq.' ')
  n=n-1
enddo
if(iflag.ne.0)a(1:1)='*'
c last minute change to reduce spaces in diagram block:
write(2,2)(a(i:i),i=1,15,2),(b(i:i),i=1,n)
2  format(132a1)
i1=i3
goto 10
99  if(i3.gt.0.or.lnSub.ne.0)then
  PRINT*,***WARNING--SOME NEST LEVELS LEFT HANGING AT END***!
  print*,char(7)
endif
end

```

C-----

logical function find(a,b,icond) !find b in a, subject to conditions:

- !icond=sum of the following:
- !1: Prior, if exists, must be blank
- !2: Must be first non-blank
- !4: Prior character, if present,
! must not be alphanumeric.
- !8: Prior character, if present,
! must be blank or)
- !16: Prior character, if present,
! must be blank or ,
- !32: Next character not alphanumeric
- !64: Next character not alphabetic
- !128:Next character must be blank or (

```

character(*) a,b
character*1 c,cNext
common icol
logical result

```

```

ii=len(a)
jj=len(b)
result=.false.
do i=1,ii-jj+1
  if(a(i:i+jj-1).eq.b)then

```

```

icol1=i           ! icol1=column of item found
icol =i+jj        ! icol =column after item found

c=' '
cNext=' '
if(icol1.gt.1)c=a(icol1-1:icol1-1)
if(icol .le.ii)cNext=a(icol:icol)

result=.true.
if(result.and.iand(icond,1).ne.0.and.icol1.gt.1)then
  result=c.eq.''
endif

if(result.and.iand(icond,2).ne.0.and.icol1.gt.1)then
  result=a(1:icol1-1).eq.''
endif

if(result.and.iand(icond,4).ne.0)
&   result=(c.lt.'0'.or.c.gt.'9').and.(c.lt.'a'.or.c.gt.'z')

if(result.and.iand(icond,8).ne.0)result=c.eq.' '.or.c.eq.')'

if(result.and.iand(icond,16).ne.0)result=
&   c.eq.' '.or.c.eq.'''

if(result.and.iand(icond,32).ne.0)
&   result=(cNext.lt.'0'.or.cNext.gt.'9').and.
&   (cNext.lt.'a'.or.cNext.gt.'z')

if(result.and.iand(icond,64).ne.0)
&   result=(cNext.lt.'a'.or.cNext.gt.'z')

if(result.and.iand(icond,128).ne.0)
&   result=cNext.eq.' '.or.cNext.eq.('

find=result
if(result)return
endif
enddo
find=result
return
end

```

C-----

```

character*5 function fm(n)      ! Format a number in i5
character*10 form
form=' '
write(form,'(i5)')n
fm=form

```

end

-----CUT HERE-----

(opinions expressed are mine alone)

Mitchell R Grunes (grunes@nrlvax.nrl.navy.mil)

Allied-Signal Tech. Serv. / Naval Research Lab
